



## Benefits

lamps are great for a variety of applications including accent lighting (interior and exterior), landscape lighting, architectural lighting, mood lighting, and more! Our full line of colored par lamps is available in Red, Green, Blue, or Amber, and comes as a Par 20, Par 30, or Par 38. With a variety of beam spreads from 15 to 38 degrees, ColorPars are incredibly versatile. Do something different for your holiday lighting, or just add a little color to your life with ColorPar!

## FEATURES

Wattages: Red & Amber 18 watt	Blue & Green: 25 watt
Life	50,000 hours
Lumens	1300 -1800
Socket	E26
Operating Temperature	-30°C to +45°C
E26 MOL	3.74in, 111.5mm
Voltage	85~265V AC
Weight	4.9 oz, 94.99g
Wildlife Friendly	ETL Listed
Warranty	5 year limited

## COLOR OPTIONS



## ORDERING INFORMATION

Model Number	Base Type	Wattage	Color (CCT)	Beam Spread	Efficacy	CRI
LVL-PAR38	E26 - Medium Base	20 - 20W	WW- Warm White NW -Natural White CW - Cool White	15 - 15° 24 - 24° 38 - 38° 60 - 60°	NA	NA
		18 - 18W	R - Red A - Amber			
		25 - 25W	G - Green B - Blue			

## ORDERING FORM

BLED-LVL-PAR38

NORTH AMERICAN



ENVIRONMENT



## CAUTIONS

THIS DEVICE IS NOT INTENDED FOR USE WITH EMERGENCY EXITS. NOT FOR USE IN TOTALLY ENCLOSED FIXTURES. PERFORMANCE MAY DECLINE DUE TO TYPE OF FIXTURE ENCLOSURE. CAUTION: RISK OF SHOCK - DO NOT USE WHERE DIRECTLY EXPOSED TO WATER. TURN OFF POWER BEFORE INSPECTION, INSTALLATION, OR REMOVAL. DO NOT OPEN - NO USER SERVICEABLE PARTS INSIDE. Suitable for damp locations. Use only on 120 volt, 60 Hz circuits. This device complies with part 15 of the FCC rules and has been tested and found to comply with the limits for a class B digital device. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. Any changes or modifications not expressly approved by the manufacturer could void the user's authority to operate the equipment. For use with light dimmers. Compatible with most dimmer switches.